

D2N/2 Emergency Output Chart

Load Voltage	Em Wattage (EOF Watts)	Em Current (EOF Milliamp)
10	4.00	400
11	4.20	382
12	4.40	367
13	4.55	350
14	4.70	336
15	4.74	316
16	4.78	299
17	4.82	284
18	4.86	270
19	4.88	257
20	4.90	245
21	4.91	234
22	4.92	224
23	4.93	214
24	4.94	206
25	4.95	198
26	4.96	191
27	4.97	184
28	4.98	178
29	4.99	172
30	5.00	167
31	5.00	161
32	5.00	156
33	5.00	152
34	5.00	147
35	5.00	143
36	5.00	139
37	5.00	135
38	5.00	132
39	5.00	128
40	5.00	125
41	5.00	122
42	5.00	119
43	5.00	116
44	5.00	114
45	5.00	111
46	5.00	109
47	5.00	106
48	5.00	104
49	5.00	102
50	5.00	100
51	5.00	98
52	5.00	96
53	5.00	94
54	5.00	93
55	5.00	91
56	5.00	89
57	5.00	88
58	5.00	86
59	5.00	85
60	5.00	83
61	5.00	82
62	5.00	81
63	5.00	79
64	5.00	78
65	5.00	77
66	5.00	76
67	5.00	75
68	5.00	74
69	5.00	72
70	5.00	71
71	5.00	70
72	5.00	69
73	5.00	68
74	5.00	68
75	5.00	67
76	5.00	66
77	5.00	65
78	5.00	64
79	5.00	63
80	5.00	63