

TLP/2 Emergency Output Chart

Load Voltage	Em Wattage (EOF Watts)	Em Current (EOF Milliamp)
50	4.40	88
55	4.40	80
60	4.40	73
65	4.40	68
70	4.40	63
75	4.40	59
80	4.40	55
85	4.40	52
90	4.40	49
95	4.40	46
100	4.40	44
105	4.40	42
110	4.40	40
115	4.40	38
120	4.40	37
125	4.40	35
130	4.40	34
135	4.40	33
140	4.40	31
145	4.40	30
150	4.40	29
155	4.39	28
160	4.39	27
165	4.38	27
170	4.37	26
175	4.37	25
180	4.36	24
185	4.35	24
190	4.35	23
195	4.34	22
200	4.33	22
205	4.33	21
210	4.32	21
215	4.31	20
220	4.31	20
225	4.30	19
230	4.29	19
235	4.29	18
240	4.28	18
245	4.27	17
250	4.27	17
255	4.26	17
260	4.25	16
265	4.25	16
270	4.24	16
275	4.23	15
280	4.23	15
285	4.22	15
290	4.21	15
295	4.21	14
300	4.20	14